

# SF-BNC4K-HDMI

BNC to HDMI Converter

1 BNC input

1 HDMI 1080p output

1 BNC output (loop with BNC in)

Output resolution 1080p

Video input resolution up to 8 MP



Safire

BNC to HDMI Converter

1 BNC input

1 BNC output

1 HDMI 1080p output

Input resolution up to 8 MP

Input format TVI / CVI / AHD / CVBS

75 ohm and high impedance

Possibility of loop between BNC

# Specifications

<b>Brand</b>	Safire
<b>Input</b>	1 BNC input
<b>Output</b>	1 HDMI output / 1 BNC output
<b>Loop between BNCs</b>	Support
<b>Input resolution</b>	8 Mpx (HDTVI) / 8 Mpx (HDCVI) / 5 Mpx (AHD) / 1080p (CVBS)
<b>Output resolution</b>	HDMI 1080p
<b>Audio</b>	No
<b>Functions</b>	Test of analog cameras up to 8 MP
<b>Output Impedance</b>	75 ohm / Hi-Z
<b>Power</b>	5VDC / 2 at max.
<b>Working conditions</b>	-25 ° ~ 75 °
<b>Dimensions</b>	20 (H) x 55.0 (W) x 66 (D) mm