

SF-MNT10BNC

Monitor SAFIRE LED 10"

Designed for surveillance use

Format 16:10

VGA, HDMI, BNC loop and Audio

Resolution 1280x800

Integrated speakers



Safire

LED monitor 10"

Specific for CCTV

Format 16:10

Number of colours 16.7 M

Resolution 1280x800

Brightness 300 cd/m²

Image contrast ratio 800:1

Response time 8 ms

1 BNC input / 1 BNC video output (loop)

Additional video inputs: VGA and HDMI

1 input audio jack 3.5 mm

Speakers built-in

Without image distortion

Specifications

Size (inches)	10.1"
Number of colours	16.7 M
Resolution	1280x800
Viewing angle	160°
Brightness	300 cd/m2
Contrast ratio	1200:1 (Typical) 50.000.000:1 (Dynamic contrast)
Response time	8 ms
VESA Bracket	75x75
Special features	Multilingual OSD menus / 3D-NR / Video BNC loop
Audio	Jack input 3.5mm Stereo
Input / Output	D-Sub (VGA), HDMI, BNC IN / BNC OUT
Signal frequency	60~75 Hz(V)
Energy consumption	15W
Power	12V DC / 3A
Dimensions (without bracket)	246 (Length) x 43 (Width) x 173 (High) mm
Dimensions (with bracket)	246 (Length) x 85 (Width) x 230 (High) mm